



# HELIOS TUBE

## CHARGING CASE

Case to charge and carry 8 tubes and their main accessories  
FP2-CHRCSE



### Electrical

(Via FP1-PWB)  
Input Voltage  
90~250VAC

Current  
4.4A @ 115VAC  
3A @ 230VAC

Output Voltage  
10 x 24 VDC

Output Current  
10 x 2A

Power in  
Via Powercon True1

Power out  
Via Powercon True1

### Construction

Material  
ABS

Operating Temperature  
0-40 °C  
32-104 °F







Weight (empty)  
15kg | 33.06lbs

Weight (full)  
31kg | 61.34lbs

Dimensions  
765 x 503 x 260mm  
30.11 x 19.80 x 10inches

Environment  
Indoor | Outdoor

### Included in the set

-  PowerBox (x1)  
FP1-PWB (+ 1x Powercon True1 cable  
+ 8x DC connection cables)
-  Helios Tubes (x8)  
FP2
-  Eyebolts (x16)  
AX1-EBLT
-  Clamp (x16)  
AX1-H
-  Stands (x8)  
AX1-STD
-  BabyPin (x16)  
AX1-BLT

### Also can hold

-  WingPlates (x8)  
AX1-WP

**Note:** The Helios Tube Charging Case is available in 2 versions:  
- Set (order code: FP2-SET)  
- Case (order code: FP2-CHRCSE)

### Included in case

Included Connectors/Cables  
1 x Powercon True1 cable  
8x DC connection cables

### Drawings

